

## ZG RETROFIT BOX W

### Zhaga socket retrofit box wall mount

Art. no. 96684002

#### Application

The ZG RETROFIT BOX M and ZG RETROFIT BOX W are accessories designed to interface between non-Zhaga D4i luminaires and a Zhaga-D4i wireless controller. These accessories can be either attached to a mast (M version) or to wall (W version).

The ZG RETROFIT BOX M & W are part of THORN UrbaSens PLAY control system.

The ZG RETROFIT BOX M & W are only compatible with RF-Controller ZG bDW 96636993



#### Functional description

Functional description:

- Integrated 24V Power supply
- Integrated DALI bus power supply
- Integrated 10kV surge protection
- ZU Zhaga book 18 ed 3.0 socket

#### Technical data

Nominal input voltage	220-240 V
Permitted input voltage	198-264V
Outputs	1 D4i compliant output with integrated bus power supply (DA+/DA-)
Power consumption	Max 8 DALI loads
Ambient temperature	-20°C to +50°C
Degree of protection	IP 66
Impact strength	IK08